




This is the high tech heart of the FX Luminaire low voltage lighting system. The PX is available in 300, 600 and 900 Watt capacities with a variety of control options. The enclosure is fabricated from heavy gauge stainless steel for long life in corrosive exterior locations.

PX: Transformer

MODELS:	300, 600 or 900 Watt
FINISHES:	Stainless Steel or Powder Coat Finishes
ACCESSORY:	Timer and/or Photocell
DEPTH:	6" / 15.24 cm
WIDTH:	7.5" / 19.1 cm
HEIGHT: (300 & 600 Watt)	13.5" / 34.3 cm
(900 Watt)	16.5" / 41.9 cm



ORDERING INFORMATION



PX: Transformer

FACTORY INSTALLED OPTIONS: Order 1 + 2 + 3 + 4

Step	Description	Code
1	TRANSFORMER	PX
2	SIZE	300, 600, 900 (Watts)
3	OPTIONAL SWITCHING	T (Timer), PC (Photocell), or TPC (Timer & Photocell)
4	FINISH	SS, WG, FW, AL, BZ, DG, WI, VF, SB, FB

EXAMPLE: PX-300-SS = PX Transformer -300W - Stainless Steel Finish

FIELD INSTALLED OPTIONS: Order Individually


Description	Code
FIXTURE	PXSYNC (PX Sync Lighting Synchronizer for 24V for Irrigation Controllers, 2.75" w x 3" h x 1.5" d)

EXAMPLE: PXSYNC = PX SYNC Lighting Synchronizer



PX FEATURES

- **Stainless Steel Construction:** No plated common steel is used which means no rust
- **Open Switching Control Architecture:** Any standard timer, photocell, manual switch, or "smart home" device may be used
- **Extra Large Terminal Block:** Each terminal can handle up to 16 12-gauge conductors
- **Nickel-plated Terminal Block Hardware:** The ultimate conductive surface to minimize resistance
- **Aerospace Circuit Breakers:** These breakers are not temperature sensitive which minimizes nuisance tripping so the transformer can be fully loaded
- **Two-Inch Conduit Knock-Out:** Allows installer to bring up to 20 cables to the terminal block
- **Industry Leading Warranty:** 10-year warranty for extra assurance

METALS



POWDER COAT



The PX comes standard in stainless steel, with a 3' power cord, choice of timer and/or photocell.

SAFETY STANDARDS

ETL Listed to UL Standards For Safety:
 PX300 - UL1838
 PX600 - ETL1838/379
 PX900 - ETL1838/379
 UL1838 Standards
 UL379 Standards



For high performance and predictable lamp life use FX LUMINAIRE Transformers only. The PX is specifically designed for the high tech lamps used in our fixtures — the use of inferior power supplies can cause premature lamp failure and other problems including the risk of fire. For more information on this very important subject please contact us at 760.744.5240.

