Z-SPRAY



	ZS-5260 Z-Max (shown)	ZS-4630 Intermediate	ZS-4230 Junior	ZS-3624 Junior 36	ZS-3620-R JR36R
Engine	16HP Briggs Vanguard				13HP Honda
Transmission	Hydro	Gear BDP-10L Pur	mp, Dan Foss Whe	el Motors	Hydro Gear Direct Drive Pump
Performance	8 MPH (forward) ~ 4.5 MPH (reverse)				
Spray Tanks	2-30 gal.	2-15 gal.	2-15 gal.	24 gal.	20 gal.
Pump	Delavan 4GPM Electric Diaphragm Pump				
Boom Hose	10' 3-Section Boom	8' 3-Section Boom	8' 3-Section Boom	8' 3-Section Boom	8' 3-Nozzle Boom
Hose	75' Hose & Cox Reel				25' Coil Hose
Spray Coverage	240,000 sq. ft.	120,000 sq. ft.	120,000 sq. ft.	96,000 sq. ft.	80,000 sq. ft.
Spreader Capacity	220 lb.	220 lb.	120 lb.	120 lb.	120 lb.
Spread Width	3' to 25' with variable speed controller				
Dimensions (L x W x H)	73" x 52" x 50"	73" x 46" x 50"	73" x 42" x 50"	73" x 35½" x 50"	49" x 35½" x 54"
Weight	892 lb.	857 lb.	819 lb.	776 lb.	521 lb
Warranty*			1 Year		

*Consult Owners Manual for full warranty details

တ	JDL-ZL - Large Hopper Cover	Fits Max & Intermediate
Optional Accessorie	JDL-ZS - Small Hopper Cover	Fits Junior, Junior 36, & JR36R
	Various skus	Equipped with its own pump & hose, this system can be used for many additional applications
	Various skus	Increase machines sprayer capacity
	Various skus	Avoid uneven overlap & save on product costs
	Various skus	Increase spray capacity by 33% [Z-Max ONLY]
	80928 - Liquid Rate Controller	Apply the proper amount of chemical despite ground speed
	90131 - Carrying Rack	Fits into receiver hitch for easy transport of the unit (JR36R ONLY)
	Various - Spare Parts Kit	Eliminate downtime with these kits packed with commonly used parts.

